



Kurz-Kasch, Inc.

Electronics Division
 Box 1246
 1501 Webster Street
 Dayton, Ohio 45401
 Telephone (513) 223-8161

Operating Instructions

For Model

282A, 283B

SEA WOLF II

MIDWAY

	SL2			START 2			SR2		5V				
		X			X			X					
LLP	SL1	SL5	SL3	LRP		RLP	SR1	SR5	SR3	RRP	ON	OFF	
		X	X				X	X	X				
X				X	X	X				X			
		SL4						SR4					
		X						X					
	SL6		SL7		COIN		SR6		SR7		POWER		
	X		X		X		X		X	X			
											ON	OFF	

1. Install the 283B card into the program B connector, number side up.
2. Connect the two molex connectors to the Mother Board.
3. Connect the alligator clip to the ground strap coming from the test fixture.
4. Set monitor selector switch, SW-7 on game board, to ON for black and white video.
5. Install the 282A card into the program A connector, number side up.
6. Connect the three Molex connectors to the game board.
7. Connect speakers to the speaker leads.
8. Slide the 5V switch to ON.
9. Slide the Power switch to ON.
10. The switch on the 283B card is reset.
11. Press COIN to coin the game.
 Press START 1 for a one player game.
 Press START 2 for a two player game.
12. SR-5 fires the right torpedo.

Combinations of SR-1 through SR-7, except SR-5, aim the right torpedo.

SL-5 fires the left torpedo.

Combinations of SL-1 through SR-7, except SL-5, aim the left torpedo.