



Kurz-Kasch, Inc.

Electronics Division
Box 1246 • 2271 Arbor Blvd.
Dayton, Ohio 45439
Telephone (513) 299-0990

Operating Instructions

For Model

313ABC

HEAD-ON

GREMLIN

	SL2				START 2			SR2				5V	
LLP	SL1	x	SL3	LRP	x	x	RLP	SR1	x	SR3	RRP	ON	OFF
		SL5			START1			SR5					
x	x	x	x	x	x	x	x	x	x	x	x		
		SL4						SR4					
		x						x					
	SL6		SL7		COIN			SR6		SR7		POWER	
	x		x		x			x		x	x		
												ON	OFF

1. Insert 313B card in TF-650 "B" port, number side up.
2. Insert 313A card in TF-650 "A" port, number side up.
3. Insert 313C card in TF-650 "C" port, number side up.
4. Connect cables from "C" card to HEAD-ON board.

10 pin molex (5 wires) to power connector
 8 pin molex (2 wires) to video connector
 10 pin molex (7 wires) to P-1 connector
 15 pin molex (5 wires) to coin door connector.

5. Turn on 5VDC and then power switch on TF-650.
6. Controls are as follows:

Coin - COIN
 SR-5 - SPEED

These are screen directions:

SR-1 - CAR LEFT
 SR-2 - CAR UP
 SR-3 - CAR RIGHT
 SR-4 - CAR DOWN

7. Switch on "A card" (advert) is the advertising switch-This should be in OFF position for test.
8. The COIN LED on "A card" should FLASH each time "COIN" on TF-650 is pushed.